



## FEATURES



### **OHV**

Over Head Valve easy to maintenance



### **OIL LEVEL ALARM**

When the oil level is low that the engine will not start. voltage of a generator.



### **AVR**

AVR is a device often solid state, for controlling the output



### **CIRCUIT PROTECTOR**

Circuit Protector is a device capable of carrying and interrupting both load and fault current upto a certain rating.



### **VOLTMETER**

It is a gauge for out put voltage of generator set.



### **CHOKE SYSTEM**

engine.

## GENERAL SPECIFICATIONS

Mono-Phase, 50 Hz, PF 1

AC Rated Power (kW)	1,7
Maximum Power (kW)	1,9
AC Rated Current	7,7
DC Rated Current (A)	6
Voltage (V)	230
Frequency (Hz)	50
Phase N.	1
Power Factor	0,80
Fuel Consumption (L/h.)	1,1
Run Time (Hour)	5
Noise Level (dB(A))	64



## ENGINE SPECIFICATIONS

Speed (Rpm)	3000
Cylinder N.	1
Oil Capacity (L.)	0,4
Fuel Type	Gasoline
Fuel Tank Capacity (L.)	3,2
Start Type	Rope

## DIMENSIONS AND WEIGHT

Width (mm.)	550
Lenght (mm.)	305
Height (mm.)	460
Dry Weight (kg.)	24,3